

# 4" LED Bi-Pin Retrofit Insert Baffle Trims




## Features

- Perfect for retrofitting Low Voltage Housings to LED.
- GU5.3 socket for MR16 retrofit.
- Baffle reduces stray light.
- Flicker free dimming.

## Specifications

<b>Wattage</b>	9W
<b>Lumens</b>	600 lm
<b>Voltage</b>	12V
<b>Color Temp.</b>	2700K, 3000K, 3500K, 4000K, 5000K
<b>Dimmable</b>	Triac/ELV
<b>Lamp Type</b>	LED
<b>CRI</b>	90+
<b>Damp Location Listed</b>	

## Dimensions



## Technical Details

### Construction:

- Meticulously manufactured trim with a powder coated or anodized finish.
- Diecast trim ring for durability and lasting quality.
- Baffle helps reduce glare.

**Installation:** Clips securely mount trim into the housing and keeps ring flush with ceiling.

**Compatible Housing:** Compatible with 4" Low Voltage IC and Non-IC versions with GU5.3 base.

**Dimmability:** Dimmability depends on transformer compatibility (magnetic or electronic).

## Product Number

Item	Lamp type	Lumens	CCT	Watts	Voltage	Dimming	Finish
<b>EL140CT5W</b>	LED	600 lm	2700K, 3000K, 3500K, 4000K, 5000K	9W	12V	Triac/ELV	White

## Product Number Builder Example: EL140CT5W

4" LED Bi-Pin Retrofit Insert

Color Temp.

Finish

**EL140**

**CT5** 2700K - 5000K

**W** White



**ELCO Lighting**

# Dimmer Compatibility Chart

## 4" LED Bi-Pin Retrofit Insert

With Electronic Low Voltage Transformers

### For Reference Only

Testing conducted by ELCO Lighting is not a substitute for and does not imply certification by an independent laboratory or any other standards certification. Refer to manufacturer specifications for more detailed information on product certifications and standards. Consult the dimmer manufacturer prior to installation to ensure compatibility.

Manufacturer	Product	Part Number	Dimmed Light Output Range
<b>ELV Dimming</b>			
Lutron	Diva® 300W Single-Pole Electronic Low Voltage Dimmer	DVELV-300P	10% - 100%
	Diva® 300W 3-Way Electronic Low Voltage Dimmer	DVELV-303P	10% - 100%
	Skylark® 300W Single-Pole Electronic Low Voltage Dimmer	SELV-300P	10% - 100%
	Skylark® 300W 3-Way Electronic Low Voltage Dimmer	SELV-303P	10% - 100%
	Maestro® 600W Single-Pole/Multi-Location Electronic Low Voltage Dimmer	MAELV-600	10% - 100%
Leviton	SureSlide® 300W 3-Way Electronic Low Voltage Dimmer	6615-P0	10% - 100%
	Decora® 450W Single-Pole/3-Way Electronic Low Voltage Dimmer	DSE06-10Z	10% - 100%
	IllumaTech® 300W Single-Pole/3-Way Electronic Low Voltage Dimmer	IPE04-1LZ	10% - 100%
	Vizia® RF + 600W Single-Pole/3-Way/Multi-Location Electronic Low Voltage Dimmer	VRE06-1LZ	10% - 100%
	Vizia® 600W Single-Pole/3-Way/Multi-Location Electronic Low Voltage Dimmer	VZE06-1LX	10% - 100%
	Decora® Digital Bluetooth 600W Single-Pole/3-Way/Multi-Location Electronic Low Voltage Dimmer	DDE06-BLZ	10% - 100%

\*NOTE: Refer to dimmer manufacturer's documentation for installation instructions and circuit details

Disclaimer: Minimum and maximum loads for LEDs and CFLs are given in number of lamps and may vary depending on the lamp being used. Testing conducted by ELCO Lighting is not a substitute for and does not imply certification by an independent laboratory or any other standards certification. Refer to manufacturer specifications for more detailed information on product certifications and standards.