NLCBC-569 5" Cobalt LED Adjustable Retrofit Source: 14W LED Up to 1200lm

PRODUCT DESCRIPTION

Cobalt retrofit series is cULus classified for use in existing IC or Non-IC housings manufactured by Nora and others. Patented adjustable mechanism rotates and adjusts while never exposing an opening or breaking the ceiling plane. Retrofit luminaires deliver up to 1200 lumens in various color temperature options. Cobalt series integrates the latest COB LED technology, giving bright spectacular light output and low power consumption.

FEATURES

- Retrofit existing 5" recessed housings
- Field adjustable beam spreads
- (flood installed, spot and narrow flood included) Up to 1200 lumen output
- 2700K, 3000K, 3500K or 4000K @ 90+ CRI
- COB LED Technology
- Integral dimmable driver
- Includes medium base socket adapter
- ENERGY STAR certified

SPECIFICATION

Trim: Aluminum spun reflector with deep set diffused lens for excellent visual comfort while providing high lumen output. Adjustable design rotates and adjusts while never exposing an opening or breaking the ceiling plane. Reflector places the LED optics deeper than the standard increasing the visual comfort. Additionally the deep cones reduces board images when off.

Adjustability: 358° rotation and 30° tilt

Optics: Spot (included), Medium (included) and Flood optic (installed)

Lens: Frosted Lens (installed) and Semi-Frosted Lens (included)

ELECTRICAL

Input Voltage: 120V

Lumens / Wattage: Up to 1200Im / 14W

(Delivered lumens will vary depending on CCT, optic & finish) Color Temperature: 2700K, 3000K, 3500K or 4000K Color Rendering Index: 90+CRI

Beam Spread: 23° Spot, 50° Narrow Flood, 99° Flood

Operating Temperature: 0°C to 25°C

Life Expectancy: 54,000 Hours @ L70

Dimming: Triac or ELV

Click Here or check complete dimmer list at www.NoraLighting.com in the "Compatibility" page under "Resources" tab

COMPATIBLE HOUSINGS

Cobalt retrofit reflectors are compatible with most 5" IC and Non-IC housings by Nora and others.

Fire Box **NFBIC-5LMRATA*** NFBIC-5INCATA

ICAT Dedicated LED ICAT Line Voltage

ICAT Dedicated LFD

ICAT Line Voltage

ICAT GU24

Shallow ICAT Dedicated LED

ICAT Dedicated LED for EM

ICAT Dedicated LED, 277V

Shallow ICAT Line Voltage

New Construction

NHIC-527LMRAT* NHIC-5LMRAT* NHIC-5LMRAT/EM* NHIC-5LMRAT/277* (includes step-down transformer) NHIC-527QAT NHIC-5010AT NHIC-5G24ATFL

Remodel

NHRIC-527LMRAT* NHRIC-5LMRAT* NHRIC-5270AT NHRIC-5040AT NHR-504Q

Shallow ICAT Dedicated LED ICAT Dedicated LED Shallow ICAT Line Voltage ICAT Line Voltage Non-IC Line Voltage

* Nora Dedicated LED housings are cULus listed for use only with Nora LED Retrofits.

Retrofit: Cobalt retrofit series includes medium base screw-socket adapter (NRA-211SM) for retrofitting into existing medium base downlight housings. GU24 socket adapter is available for use with GU24 housings, must specify <u>NRA-212SM</u>.

ACCESSORIES

NLCBC-569TIR15: 15° Premium TIR optics, must specify ring finish

NLCBC-50R: Oversize ring up to 7", must specify finish.

LABELS AND LISTINGS

- cULus classified for Damp Locations when used with compatible housing
- Suitable for Type IC and Non-IC
- Certified to the high efficacy requirements of California Title 24 JA8-2022
- ENERGY STAR certified (not BB or BZBZ finish)
- RoHs Compliant
- 5-Year Limited Warranty



Туре

Project

Catalog No.

Notes

Performance Data		
Lumens	ССТ	
1092lm	2700K	
1203lm	3000K	
1206lm	3500K	
1254lm	4000K	
	1092lm 1203lm 1206lm	

Delivered lumens will vary depending on CCT, optic and finish



R7R7

PATENT No.:

D917,090S

RR Black Reflector Black Flange








H7N Haze Reflector Natural Metal Flange

HZW Haze Reflector White Flange



MPW Matte Powder White Reflector Matte Powder White Flange

ww White Reflector White Flange



5" Cobalt LED Adjustable Retrofit Optional Accessories Color Temperature Reflector Finish / Flange Finish Dimming & Emergency Description Ring Finish NLCBC-56927X = 2700K BB = Black Reflector / Black Flange (blank) = 120V Triac/ELV NLCBC-569TIR15 = 15° TIR Optic B = Black NLCBC-56930X = 3000K BZBZ = Bronze Reflector/ Bronze Flange BZ = Bronze EM = Remote Emergency (requires Nora EM housing) NLCBC-56935X = 3500K HZN = Haze Reflector/ Natural Metal Flange HZ = Haze NLCBC-56940X = 4000K HZW = Haze Reflector / White Flance MPW = Matte Powder White MPW = Matte Powder White Reflector / WW = White / White Matte Powder White Flange NLCBC-50R = Oversize Ring B = Black WW = White Reflector / White Flange BZ = Bronze MPW = Matte Powder White **WW** = White / White NRA-211SM = Medium base screw-in socket (included) NRA-212SM = Socket adapter for use with GU24 housings

Example: NLCBC-56927XWW = 5" Cobalt LED Adjustable Retrofit, 2700K, White Reflector / White Flange, 120V input; Triac / ELV dimming



PHOTOMETRICS

5" Cobalt LED Adjustable Retrofit

Туре


Project

Catalog No.

Notes

Test Information

Test Number: NTR11163 Part Number: NLCBC-56940SWW Beam Spread: Spot Lumens: 1236lm Wattage: 13.2W Efficacy: 93lpw CCT / CRI: 4000K / 90 CRI Spacing Criteria (0°-180°): 0.4 Spacing Criteria (90°-270°): 0.38



Illuminance at a Distance


	Distance from Luminaire	FC at Nadir	Beam Diameter
	4'	117fc	1'-8"
> 50°	6'	52fc	2'-6"
50	8'	29.2fc	3'-4"
	10'	18.7fc	4'-1"
	12'	13fc	5'
30°			

Zonal Lumen Summary % Zone Lumens Luminaire 0-30 597 48.3 0-40 849 68.7 0-60 1157 93.6 0-90 1224 99 90-180 12 1 0-180 1236 100

Candela Table	
Vertical Angles	Candela
0	1870
5	1528
15	779
25	536
35	403
45	280

Test Information

Test Number: NTR11162 Part Number: NLCBC-56940MWW Beam Spread: Narrow Flood Lumens: 1254lm Wattage: 13.1W Efficacy: 96lpw CCT / CRI: 4000K / 90 CRI Spacing Criteria (0°-180°): 0.74 Spacing Criteria (90°-270°): 0.76




Illuminance et a Distance

	Illuminance at a	Distance	
n°	Distance from Luminaire	FC at Nadir	Beam Diameter
0	4	72fc	3'-8"
0°	6'	32fc	5'-7"
0	8'	18fc	7'-5"
	10'	11.5fc	9'-4"
	12'	8fc	11'-1"

Zonal Lumen Summary % 7one Lumens Luminaire 0-30 612 48.8 0-40 871 69.4 0-60 1180 94.1 0-90 1242 99 90-180 12 1 0-180 1254 100

Test Information

Test Number: NTR11161 Part Number: NLCBC-56940FWW Beam Spread: Flood Lumens: 1107lm Wattage: 13.2W Efficacy: 84lpw CCT / CRI: 4000K / 90 CRI Spacing Criteria (0°-180°): 1.2 Spacing Criteria (90°-270°): 1.2



Illuminance at a Distance		
Distance from Luminaire	FC at Nadir	Beam Diameter
4'	31.2fc	9'-2"
6'	13.8fc	13'-11"
8'	7.8fc	18'-6"
10'	5fc	23'-1"
12'	3.5fc	27'-8"
12	01010	2. 0

....

Zonal Lumen Summary		
Zone	Lumens	% Luminaire
0-30	376	34
0-40	604	54.5
0-60	988	89.3
0-90	1095	98.9
90-180	12	1.1
0-180	1107	100

Candela Table Vertical Candela

Angles	
0	499
5	497
15	473
25	426
35	364
45	290

Lumen Output Multipliers

Color Temperature: 2700K (0.87), 3000K (0.96), 3500K (0.96), 4000K (1.00)

