


# ONYX Series

## LED Retrofit Downlight and Adjustable

Nora Lighting's new Onyx Series offers an economical, quality solution to LED Retrofit Downlighting. Deep-set optics produce visual comfort in 4" and 5"/6" apertures. The Onyx Surface Adjustable offers flexibility to highlight a focal point, wash a wall in light or use as a slope ceiling solution. The Onyx produces 90+ CRI for true vibrant color rendition. Baffle and reflector style downlights blend with popular trims and create an uniform ceiling appearance. The 4" 650 lumen/10 watt unit is compatible with Nora's dedicated housing to meet energy rebate requirements, as well as Nora's 4" medium base housings and 4" housings by others. The 5"/6" 750 lumen/ 12 watt unit is compatible with Nora's dedicated 5" and 6" housings to meet energy rebate requirements, as well as Nora's 5" and 6" medium base housings and 5" and 6" housings by others. cULus, Energy Star and Title 24 listed, the Onyx by Nora can be used in new construction, remodel and retrofit applications. Onyx is the smart choice for energy-efficient, dimmable lighting.

### FEATURES

- 5-Year limited warranty
- Downlight
  - Deep set optics
  - 4" and 5/6" Apertures
- Adjustable
  - Surface Gimbal Ring
  - 4" 18° adjustable, 5/6" 40° adjustable
- 90+ CRI
- 4" – 650 Lumen / 10 watt
- 5"/6" – 750 Lumen / 12 watt
- 2700K, 3000K and 4000K CCT
- Baffle, Reflector and Adjustable styles
- White finish
- Dimmable
- Includes Medium Base socket for easy retrofitting
- Small disconnect compatible with most dedicated housing by others
- 36,000 Hour life
- ENERGY STAR rated
- cULus listed for Wet location (Downlight)
- cULus listed for Damp location (Adjustable)
- Title 24/JA8 Compliant



Each unit includes a medium base socket



NOX-43127WW  
4" Reflector, 2700K

NOX-43230WW  
4" Baffle, 3000K



NOX-43427WW  
4" Adjustable, 2700K



NOX-563130WW  
5"/6" Reflector, 3000K

NOX-563440WW  
5"/6" Adjustable, 4000K



# ONYX SERIES 4" AND 5"/6" LED RETROFIT DOWNLIGHTS AND ADJUSTABLES

## ONYX SERIES 4", 5"/6" LED RECESSED RETROFIT

SERIES	APERTURE	TRIM STYLE	COLOR TEMP	FINISH
NOX- Onyx Retrofit	4 4" Aperture	31 Reflector	27 2700K	WW White with White Flange
	56 5"/6" Aperture	32 Baffle	30 3000K	
		34 Adjustable	40 4000K	

Example: **NOX-43127WW** - 4" Onyx Series LED Retrofit unit, Reflector, 2700K, White Reflector, White Flange  
**NOX-563430WW** - 5"/6" Onyx Series LED Retrofit unit, Adjustable, 3000K, White finish

### COMPATIBLE NORA HOUSINGS

NEW CONSTRUCTION	REMODEL
<b>NSIC-401QAT</b> 4" ICAT Line Voltage	<b>NSR-404QAT</b> 4" AT Line Voltage
<b>NS-401QAT</b> 4" AT Line Voltage	<b>NHRIC-4G24AT</b> 4" ICAT GU24
<b>N HIC-4G24AT</b> 4" ICAT GU24	<b>NHRIC-4LMRAT*</b> 4" ICAT Dedicated LED
<b>NHIC-4LMRAT*</b> 4" ICAT Dedicated LED	
<b>NHIC-4LMRAT/277*</b> 4" ICAT Dedicated LED, 277V	<b>NHRIC-504QAT</b> 5" ICAT Line Voltage
<b>NFBIC-4INCAT</b> 4" ICAT Fire Box	<b>NHR-504Q</b> 5" Line Voltage
<b>NFBIC-4LMRAT*</b> 4" ICAT Dedicated LED Fire Box	<b>NHRIC-527QAT</b> 5" ICAT Shallow Line Voltage
	<b>NHRIC-5G24ATFL</b> 5" ICAT GU24
<b>NHIC-501QAT</b> 5" ICAT Line Voltage	<b>NHRIC-5LMRAT*</b> 5" ICAT Dedicated LED
<b>NH-501Q</b> 5" Line Voltage	<b>NHRIC-527LMRAT*</b> 5" ICAT Shallow Dedicated LED
<b>NHIC-5G24ATFL</b> 5" ICAT GU24	
<b>NHIC-527QAT</b> 5" ICAT Shallow Line Voltage	<b>NHRIC-17QAT</b> 6" ICAT Line Voltage
<b>NHIC-5LMRAT*</b> 5" ICAT Dedicated LED	<b>NHRIC-17QNBAT</b> 6" ICAT Line Volt (No Bracket)
<b>NHIC-5LMRAT/277*</b> 5" ICAT Dedicated LED, 277V	<b>NHRIC-27QAT</b> 6" ICAT Shallow Line Voltage
<b>NHIC-527LMRAT*</b> 5" ICAT Shallow Dedicated LED	<b>NHR-26Q</b> 6" Line Voltage
<b>NFBIC-5INCAT</b> 5" ICAT Fire Box	<b>NHRIC-6G24ATFL</b> 6" ICAT GU24
<b>NFBIC-5LMRAT*</b> 5" ICAT Dedicated LED Fire Box	<b>NHRIC-6LMRAT*</b> 6" ICAT Dedicated LED
	<b>NHRIC-27LMRAT*</b> 6" ICAT Shallow Dedicated LED
<b>NHIC-17QAT</b> 6" ICAT Line Voltage	
<b>NHIC-17QNBAT</b> 6" ICAT Line Volt (No Bracket)	
<b>NHIC-27QAT</b> 6" ICAT Shallow Line Voltage	
<b>NH-26Q</b> 6" Line Voltage	
<b>NH-26QNB</b> 6" Line Voltage (No Bracket)	
<b>NHIC-6G24ATFL</b> 6" ICAT GU24	
<b>NHIC-6LMRAT*</b> 6" ICAT Dedicated LED	
<b>NHIC-6LMRAT/277*</b> 6" ICAT Dedicated LED, 277V	
<b>NHIC-27LMRAT*</b> 6" ICAT Shallow Dedicated LED	
<b>NFBIC-6INCAT</b> 6" ICAT Fire Box	
<b>NFBIC-6LMRAT*</b> 6" ICAT Dedicated LED Fire Box	

\* Nora LED Dedicated housings are cULus listed for use only with Nora Diamond/Cobalt/Onyx Series LED Retrofits.

\*\*Consult factory for EM options